

The BOSS CS²



Fig. 1



Fig. 2



Fig. 3



Fig. 4

To Set-up the Table:

- Place the folded table sitting on the rubber bumpers; with the heel of your hand, bump the tab between the face rest outlets and the table will open. (Fig. 1)
- Open the table part way, making sure the cables are still slack. (Fig. 2)
- Press on the long folding brace and pull on the legs at one end. (Fig. 3). Do the same on the other end. Open the table until the leg braces and table top are completely extended and unwrap any cables that may be caught on the legs.

To Set the Table Upright:

- When the table is fully opened, tilt the table upright until all four feet are on the floor (Fig. 4). Lift one end of the table, press down on the middle and tension the cables a little.



Fig. 5

To Change the Table Height:

- Press button on the leg and rotate the leg extension slightly to take the button out of alignment with the holes, but still within sight. Adjust all extensions to the desired height and turn until the button pops out of the aligned hole. (Fig. 5)



Fig. 6

To Close the Table:

- Turn the table on its side with the rubber bumpers down. Fold the table to about 90 degrees and push the legs against the plywood top.
- Store accessories as shown in Fig. 6.
- Push the two halves of your table together to lock. (Fig. 7).



Fig. 7

CAUTION

Dynamic Load Rating:

600 lbs.