# APPLICATION INSTRUCTION SHEET POSEY® FINGER CONTROL MITTS

Applicable Products: Cat. No. 2814, 2815, 2816, 2817, 2818, 2819, 2826, 2810

**DESCRIPTION OF PRODUCT:** A full padded hand mitt with or without finger separators.

CAUTION: FEDERAL LAW (USA) RESTRICTS THIS DEVICE TO SÁLE OR USE BY OR ON ORDER OF A PHYSICIAN.

#### INDICATIONS:

- Patients who continually disrupt lifesaving treatment (e.g., chronic tubepulling which breaks the integrity of an IV line or self-extubation).
- When a patient's pulling lines prevents the healthcare professional from adequately monitoring the vital signs of the patient.
- When a patient's picking, pulling, scratching or peeling exacerbates a skin condition, causes self-injury, or disrupts wound site integrity.

#### **CONTRAINDICATIONS:**

Contraindications include, but are not limited to the following conditions:

- Do not use Posey Mitts on patients with dislocations, fractures or open wounds on the affected limb.
- Do not use Posey Mitts if the I.V. site could be compromised.
- Do not use on the patient who is suicidal, highly aggressive and/or combative, who strikes and endangers himself and/or others. See Posey catalog for more suitable products.

#### **ADVERSE REACTIONS:**

Severe emotional, psychological, and physical problems may occur if a patient's movement is severely limited. The patient may become agitated if the device is uncomfortable or severely limits movement. Request assistance from a qualified medical authority to try to find a less restrictive alternative product or intervention.

### **AWARNING**

If this device is applied too tightly, circulation will be impaired; If too loose, the patient may be able to slip his/her limb from the device. Check circulation frequently and monitor for skin discoloration

Do not attach the Posey Mitt in a way that the patient may use his/her teeth to remove the device or inflict selfinjury. Additional body restraint (fifth point) may be required to prevent the patient from moving the line/wound/ tube site to within access of his/her hands. Refer to Posey Psychiatric and Emergency Dept. Product Book, Part No. M1031.) Always secure strap at a frame juncture which will not allow the straps to slide in any direction, changing the position of the product.

A patient in a supine position who cannot sit up requires extra vigilance. Should the patient vomit, he/she could aspirate his/her vomitus and suffocate. Monitor constantly and be prepared to intervene at the first sign of danger

#### Laundering Instructions:

This product was designed to be washed under CDC recommendations for linen soiled with blood or bodily fluids:



WASH HOT BLEACH AS DIRECTED ON CONTAINER



Lower temperature washing and drying cycle for non-contaminated linen will prolong product life.

The "hook" of hook and loop closure material has a tendency to collect lint after repeated use and/or laundering, reducing the grip strength of the hook and loop. Test for secure hold before each use. Discard if it does not hold securely. Occasionally go over the "hook" with a stiff brush to remove lint. Fastening the "hook" to the "loop" during laundering will also help to prevent lint buildup. (Ref: 84)

Inspect buckles regularly and discard if cracked. Do not put buckles through extractors.

ADDITIONAL SAFETY **INSTRUCTIONS ON OTHER SIDE** 









Top left: 2815 for pulse oximetry Bottom left: 2817

Top right: 2816 Bottom right: 2819

#### APPLICATION INSTRUCTIONS:

- 1) Put the patient's hand into the mitt, separating the fingers so they fit into each finger slot. (Models 2817 and 2826 have three finger separations which include a separate slot for the thumb and pinky finger. Models 2810, 2818 and 2819 have no finger slots.)
- 2) Place the strap over the smallest part of the wrist to reduce the potential of unintentional removal.
- Bring the hook and loop closure over the top of the wrist, through the plastic ring, and secure it onto itself. Model 2818 does not have plastic rings. With models 2814 and 2819, the fuzzy loop strap of hook and loop closure goes through the two slits before going through the plastic ring, and back onto the hook side. Then bring the second hook strap over the top of the fuzzy loop strap to form a "double security" closure. Model 2826 does not have a second strap.

Caution: Overtightening will compromise circulation. Leave enough room to easily insert one finger between the device and the patient's limb. Remove mitt to check circulation and range of motion at regular intervals.

If range of motion must be limited, use the extra connecting strap (included) to go through the loops or encircle the wrist, passing through the loops on the mitt. Secure to the bed with quick-release ties. (Does not apply to 2817 or 2826, which have no connecting straps.) Wrist restraints should be considered instead of the mitt if the patient pulls violently against the attachment strap.

#### Posey Padded Mitts:

Cat. No. 2811 -Peek-A-Boo Mitts

Cat. No. 2813 -Secure Mitts

Cat. No. 2814 -**Double Security Mitts** 

Cat. No. 2815 -Open End Finger Control Mitts Cat. No. 2816 -Closed End Finger Control Mitts

Cat. No. 2817 -EZ-On Mitts

Cat. No. 2818 -Mitts for Children

Cat. No. 2819 -Double Padded, Double Security Mitts

Cat. No. 2826 -**Economy Mitts** 

Cat. No. 2810 -Soft Hand Mitt

19223 010605



Posey Co. 5635 Peck Road Arcadia, CA 91006 USA Tel: 1-800-44-POSEY Fax: 1-626-443-5014 www.posev.com



Burckhardtstr. 1, 30163, Hannover, Germany





## Safety Information for the Use of Posey Torso and Limb Restrictive Products



### WARNING Monitor patients appropriately per your facility's policy!

Inappropriate and/or incorrect usage of any restrictive product may result in serious injury or death. The Posey Company recommends the following steps before any restrictive product is used

- Identify the patient's symptoms.

  Determine and remove, if possible, the cause of the symptoms. This may include catering to individual needs and customary routines; increased rehabilitation
- and restorative nursing, modifying the environment; and increased supervision. If the cause cannot be determined and removed, attempt alternative treatments
- under proper medical supervision.

  A restraint should be used only when practicable alternatives have failed. The least restrictive device that will protect the patient and others should be selected and used for the shortest time while less restrictive alternatives are sought. It is critical that the appropriate restraint is selected.
- Follow the directions on the Application Sheet accompanying each product.



#1 Posey restraints are labeled: Caution: Federal law (USA) restricts this device

to sale by or on order of a physician.

All staff should receive proper inservice training so products are applied in accordance with the manufacturer's instructions, state and federal regulations and the facility's policies and procedures. Posters, Videos and Inservice materials are available free from Posey Company



#2 Restrictive products should only be used within the carefully defined and docu-

mented parameters of the patient's Individualized Care Plan (ICP) which addresses (but is not limited to) restorative nursing, patient release, and pressure sore prevention. The ICP is created after an assessment by an interdisciplinary team which may represent (but is not limited to) PT, OT, Nursing, the Physician, and Social Services.



#3 NEVER use a Posey product as a seat belt in a moving vehicle. Posey products are not de-

signed to withstand the force of a crash.



#4 DO NOT expose any Posey Product to open fire, flame, or contact with smoking materials.

Components such as fabric, webbing, thread, etc. are susceptible to ignition and burning. The facility's smoking/no smoking policy should be vigorously enforced. Flame retardant fabric is available on request.



#5 Never crisscross the straps of a Posey Vest/Jacket in back of the patient unless

there is a positioning slot in the rear of the product. Any restraint applied incorrectly and/or worn backwards may cause strangulation or injury.

#6 Secure straps of restrictive products out of the patient's reach at a juncture of the movable part of the bed frame at waist level so the device will not tighten or loosen when any section of the bed is raised or lowered. Make sure the strap will not slide in any direction, changing position of the device.



#7 After applying a restraint or selfrelease product;

always put all side rails in the UP position.

Side rail covers, or gap protectors, especially with split side rails, may be required to keep the patient on top of the mattress, and avoid entrapment zones.



If the patient's body weight becomes suspended off the mattress by going



under, around, over, through or between the side rails, chest compression and suffocation could result.

Restraints with pelvic pieces may be necessary to reduce sliding down or pulling the restraint over their head.



#8 Hips should be held securely against the back of the chair whenever any type of restrictive product is used. The straps should be at 45

degrees over the hips and secured under the seat out of the patient's reach. Make sure straps are secured at a juncture of the frame and will not slide in any direction, changing position of the device. Use extreme caution with all cushions. If dislodged, patient injury could occur. (see #9).



#9 Monitor to make sure the patient is not able to slide down, or fall off a chair seat.

If their body weight becomes suspended off the chair seat, chest compression and suffocation could result.

Restraints with pelvic pieces may be necessary to reduce sliding down or pulling the restraint over their head.

#10 Straps must always be snug, but not interfere with breathing. You should be able to slide your open hand (flat) between the device and the patient. Make sure straps do not slide in any direction, changing position of device.

#11 Always use quick-releasing ties (see drawings) or buckles to secure straps - they allow easy release in the event of accident or fire. Restraint release should be an integral part of the facility's fire/disaster evacuation drills. Straps can be cut with scissors in an emergency.



#12 Patients in restrictive products require appropriate monitoring per your facility's policy.

Aggressive, agitated, restless patients and/or those in danger of aspirating their vomit require constant monitoring and a systematic review and evaluation of both physical and psychological status.



#13 Inspect before use for broken stitches or parts; torn, cut or fraved straps or fabric; or hook and loop fastener or

locks that do not hold securely. These products could fail, resulting in injury or death. Destroy and discard them. Straps must be long enough to secure out of the patient's reach. DO NOT alter products.



#14 Do not use Posey products on toilets, or on any type of furniture which does not allow application as directed

in the product application sheet. Posey limb and torso restraints should NOT be used at home without constant supervision of a licensed healthcare provider, physician's order and an Individualized Care Plan.

Just as patient behavior is not 100% predictable, no product is 100% foolproof under all circumstances. A restraint is not a substitute for good nursing care. Patient safety requires regular reassessment and appropriate monitoring per your facility's policy. A product that worked successfully in the past may prove inappropriate as the patient's mental and physical health status changes. Never apply any product you feel is unsafe and consult with the proper medical authority if you feel a product is inappropriate for the patient.

#### **How to Tie the Posey Quick Release Tie**

1. Wrap the attachment strap once around the movable part of the bed frame leaving at least an 8" tail. Fold the loose end in half to create a loop and cross it over the other end. Make sure straps are secured at a juncture of



the frame and will not slide in any direction, changing position of device.

2. Insert the folded strap where the straps cross over each other, as if tying a shoe or making a tourniquet knot. Pull on the loop to tighten.



3. Fold the loose end in half to create a second loop.



4. Insert the second loop into the first loop.



5. Pull on the loop to tighten.



### Sizing Table for Posey Products

Always use the proper size product. Products that are too small or large compromise patient comfort and safety and should not be used.

Binding Color	Size	Weight (lb./kg)	Chest (in./cm)
White	X-Small	60-90/27-41	28-34/71-86
Red	Small	80-120/36-54	32-39/81-99
Green	Medium	110-155/50-70	37-45/94-114
Yellow	Large	145-190/66-86	43-49/109-124
Blue	X-Large	180-230/82-104	47-52/119-132
Black	XX-Large	220-275/110-125	50-56/127-142
Yel/Blk	XXX-Large	265-305/120-139	54-60/137-152
Blu/Blk	XXXX-Large	295-340/134-155	58-64/147-163

Posey belts are not color-coded, but are also sized according to this table. Flame-retardant fabric is available on request.

Weight and size measurements give a general indication of the proper size. Individual physical characteristics should be taken into account before the medical authority determines the correct size. Refer to label on product for specific sizing indications.