TWICE-AS-TOUGH CUFFS - KEY LOCK

Applicable Products: REF 2792, 2793, 2798, 2799

DESCRIPTION OF PRODUCT: Very secure, padded limb restraints with double hook & loop closure.

Rx ONLY

2798



INDICATIONS FOR USE:

- Patients assessed to be at risk of disrupting life-saving treatments (e.g., chronic tube
- Patients assessed to be at risk of line pulling, which may prevent monitoring of vital signs.
- Patients whose picking, pulling, scratching, or peeling exacerbates a skin condition, causes self-injury, or compromises wound site integrity.
- Patients assessed as being in extreme danger of injury to themselves or to others.

CONTRAINDICATIONS:

- DO NOT use this device on a patient who is or becomes: suicidal; highly aggressive or combative; self-destructive; or deemed to be an immediate risk to others, UNLESS the patient is under constant supervision.
- NEVER use on a patient:
 - With a dislocation or fracture on the restrained limb; or
 - If an IV or wound site could be compromised by the device. See the Posey Catalog for other options for such a patient.



 Severe emotional, psychological, or physical problems may occur: if the applied device is uncomfortable; or if it severely limits movement. If the patient is likely to cause injury to him/herself or others, get help from a qualified medical authority to find an alternate intervention or method of restraint.

to cut the cuffs with scissors to free the patient.

If the patient pulls violently against the bed straps;

damaging or opening lock.

Posey Catalog):

POSEY TWICE-AS-TOUGH CUFFS

REF 2792 Wrist, pair, key lock (color coded blue)

REF 2793 Ankle, pair, key lock (color coded red) **REF** 2798 Wrist, pair, key lock cuff and strap

(color coded blue)

REF 2799 Ankle, pair, key lock cuff and strap (color coded red)

APPLICATION INSTRUCTIONS: (Connecting Straps) (repeat steps 1-3 for each side)

- Before each use, check cuffs and straps for cracks, tears, and/or excessive wear or stretch; cracked or broken buckles or locks; and/or that hook and loop adheres securely, as these may allow patient to remove cuff. Discard if device is damaged.
- If you have any questions about patient safety, ask the appropriate medical authority for alternatives.
- **1.** Position the patient on the bed.
- 2. Bring the ends of the strap down through the inside of the side rails so they do not interfere when the side rails are raised. Thread the end of the strap over the top, around the frame, and through the lock. Make sure that the straps are attached to a movable part of the bed frame, out of the patient's reach.
- 3. Pull the strap snug and close the lock. Check that the lock "clicks" shut. If a lock is not completely closed, it can pop open. Before leaving the patient's side, test the lock by trying to open it without the key.

APPLYING THE CUFFS (repeat steps 1-3 for each limb):


- 1. Wrap the neoprene piece (the blue or red side should be positioned against the skin) around the wrist/ ankle. Attach the black hook and loop pieces together, followed by the blue or red hook and loop pieces. The fuzzy piece should be sandwiched between the two pieces of hook (fig. 1). Be sure to overlap at least one inch (3 cm).
- 2. Press the hook and loop closure together firmly and make sure it adheres securely. Slide ONE finger (flat) between the cuff and the inside of the patient's wrist to ensure proper fit. The cuffs must be snug enough to prevent escape, but not interfere with circulation.

3. 2792, **2793**-Pass the end of the limb strap over the top of the cuff and through the two D-rings on the cuff.

Bring the strap back over the first ring and through the two D-rings on the cuff (fig. 2). 2798, 2799-Pass the end of the short strap through the lock and adjust it to the desired length. Check that the lock "clicks" shut. If a lock is not completely closed, it can pop open. Before leaving the patient's side, test the lock by trying to open it without a key. Posey Keylock Counterclockwise TO OPEN

TO UNLOCK CUFFS:

1. Insert the Posey Key into the lock and turn counterclockwise. This will prevent jamming (fig. 3). NOTE: Universal Posey Keys fit all Posey locks. To order extra keys, contact Posey at 1.800.447.6739, press 5, and ask for Cat. # 1074.





OPEN

FIG. 3

• To prevent the patient from flailing or bucking up and down and causing self-injury.

MONITOR PER FACILITY POLICY. Check to ensure that: • Straps cannot slide in any direction, tighten or loosen if the patient pulls on them, or if the bed is adjusted;

Posey Keys MUST be readily available to staff at all times. In an emergency, it is difficult

NOTE: Keep excess strap out of reach to prevent patient from pulling strap and

• To reduce the risk of the patient getting access to the line/wound/tube site;

ADDITIONAL OR DIFFERENT BODY OR LIMB RESTRAINTS MAY BE NEEDED (See

- Cuffs are attached in a way that the patient is not able to use his or her teeth or otherwise remove the device;
- Cuffs are intact, and not torn or damaged. DO NOT allow patients to ingest product material.

MONITORING

- Posey recommends constant direct supervision for patients deemed to be at risk of injury to themselves or others. For times when direct supervision is not possible, monitor by line of sight or by a video/audio device.
- NEVER allow a patient to have access to any tool, utensil, or object that might be used to unlock or damage cuffs.
- Be aware that a sudden mood swing may cause agitated or aggressive behavior. Contact the medical team AT ONCE if this occurs. No level of monitoring may avoid the risk of serious injury to highly agitated or aggressive patients.
- Check the patient regularly to ensure that:
 - Circulation is not impaired. Serious injury may occur if the cuffs restrict
 - Cuffs are secure. Death or serious injury to the patient or others may occur if the patient can remove the cuffs.

RFD SAFFTY

pads and/or gap

protectors to cover gaps.

 ALWAYS use Hospital Bed Safety Workgroup (HBSW) (http://www.fda.gov/cdrh/beds/modguide.html) compliant side rails in the UP position and fill ALL gaps to reduce the risk of entrapment.



• Use side rail covers and gap protectors to help prevent the patient's body from going under, around, through or between the side rails. A failure to do so may result in serious injury or death if a patient becomes suspended or entrapped. Posey offers a full range of side rail

ADDITIONAL SAFETY AND LAUNDERING **INSTRUCTIONS ON OTHER SIDE**







Safety Information for the Use of Posey Torso and Limb Restraining Products



MARNING: ALWAYS Monitor patients per facility policy.

Improper application or use of any restraint may result in serious injury or death.

RX ONLY. NOT FOR HOME USE. Federal law (USA) restricts this device to sale by or on order of a physician. For use in a licensed healthcare facility only.

STAFF TRAINING: Staff must have on going training and be able to demonstrate competency to use this device in accord with: Posey instructions; your facility policies and state and federal regulations (Federal Register, Part IV, 42 CFR Part 482.13(e)(5) and (f)(6); Posey offers inservice training aids at no charge. Contact Posey online at www.posey.com or call toll-free at 1.800.447.6739 (press 5).

SELECTING THE RIGHT POSEY PRODUCT: Refer to the Posey catalog to help select the right device to meet individual patients' needs.

BEFORE APPLYING ANY RESTRAINT:

- Make a complete assessment of the patient to ensure restraint use is appropriate.
- Identify the patient's symptoms and, if possible, remove the cause. You may need to: cater to individual needs and routines; increase rehabilitation and restorative nursing; modify the environment; or increase supervision.
- Use a restraint only when all other options have failed. Use the least restrictive device, for the shortest time, until you find a less restrictive alternative. Patients have the right to be free from restraint.
- Obtain informed consent from the patient or guardian prior to use. Explain the reason for restraint use to the patient and/or guardian to help ensure cooperation.
- A restraint must only be used in accord with the patient's Individualized Care Plan (ICP). The ICP is an assessment by an interdisciplinary team, which may include, but is not limited to: PT, OT, Nursing, the Physician, and Social Services. The ICP should include: restorative nursing; patient release; and pressure sore prevention.



NOTE: Just as patient behavior is not 100% predictable, no product is 100% foolproof. Patient safety requires regular reassessment and monitoring per facility policy. A product that worked in the past may be inappropriate if the patient's mental or physical health status changes. NEVER apply any product that you feel is unsafe. Consult with the proper medical authority if you have questions about patient safety.



ADDITIONAL WARNINGS:

- ALWAYS monitor patient per facility policy. Be aware that constant monitoring may be required for:
 - Aggressive or agitated patients; and
 - Patients deemed at risk of aspirating their vomit. This includes
 patients in the supine position, or who are not able to sit up. If the patient vomits, he
 or she could aspirate the vomit and suffocate.
 - Be prepared to intervene at the first sign of danger. Such patients require frequent review and evaluation of their physical and psychological status.

How to Tie the Posey Quick-Release Tie











- Wrap the strap once around a movable part of the bed frame leaving at least an 8" (20 cm) tail. Fold the loose end in half to create a loop and cross it over the other end.
- 2. Insert the folded strap where the straps cross over each other, as if tying a shoelace. Pull on the loop to tighten.
- 3. Fold the loose end in half to create a second loop4. Insert the second loop into the first loop.
- Insert the second toop into the first toop.
 Pull on the loop to tighten. Test to make sure strap is secure and will not slide in any direction
- Repeat on other side. Practice quick-release ties to ensure the knot releases with one pull on the loose end of the strap.


- 2. NEVER alter or repair this product. ALWAYS Inspect before each use: Check for broken stitches or parts; torn, cut or frayed material; or locks, buckles, or hook and loop fasteners that do not hold securely. DO NOT use soiled or damaged products. Doing so may result in serious injury or death. Dispose of damaged products per facility policy for BIOHAZARDOUS material.
- 3. ALWAYS secure straps, to a movable part of the bed or chair frame, out of the patient's reach, using quick-release ties (see drawing below) or buckles. These allow easy release in the event of an accident or fire. Test to make sure straps cannot tighten, loosen, or slip and create excess slack. If this occurs, the patient may slide off the chair or bed, increasing the risk of serious injury or suffocation. Restraint release is an important part of facility fire and disaster drills. Straps can be cut with scissors in an emergency.
- NEVER use Posey products on toilets, or on any chair or furniture that does not allow proper application as directed in the Application Instructions. DO NOT use at home.
- 5. NEVER expose this product to open flame, fire, smoking materials, or high heat sources. Some products may melt or ignite and burn. The facility smoking/no smoking policy should be strictly enforced.
- NEVER use a Posey product as a seat belt in a moving vehicle.
 Posey products are not designed to withstand the force of a crash or sudden stop.



LAUNDERING INSTRUCTIONS (if applicable):

- Fasten all buckles and locks to reduce risk of damage during wash and dry cycles. DO NOT put buckles or locks through extractors. For maximum life, launder in a laundry bag.
- Before laundering, zip up and turn the product inside out to protect zipper.
- Hook and loop fasteners may collect lint after repeated use or laundering, reducing grip strength. Fasten the "hook" to the "loop" before laundering to help prevent lint buildup. As needed, use a stiff- bristle brush to remove lint from the "hook" side.
- These products, other than foam products, can be machine washed under CDC* guidelines for material soiled with blood or bodily fluid.





product life. | 100 F | 280 C | 280 C

AWARNING

Test Zippers or hook and loop fasteners before each use. DISCARD device if it does not fasten securely.

STORAGE AND HANDLING:

- This device is designed for use in normal indoor environments.
- This device may be stored in ambient warehouse temperatures at normal humidity levels.
 Avoid excess moisture or high humidity that may damage product materials.

*www.cdc.gov

Sizing Table for Posey Products

ALWAYS use the proper size product. Products that are too small or large may compromise patient comfort and could result in severe injury or death.

BINDING COLOR	SIZE	WEIGHT lb. (kg.)	CHEST in. (cm)
White	X-Small	60-115 (27-52)	25-32 (64-81)
Red	Small	112-160 (51-73)	31-37 (79-94)
Green	Medium	135-203 (61-92)	35-40 (89-102)
Yellow	Large	160-225 (73-102)	38-44 (97-112)
Blue	X-Large	180-247 (82-112)	42-48 (107-122)
Black	XX-Large	220-275 (100-125)	46-55 (117-140)
Yellow/Black	XXX-Large	265-305 (120-138)	54-60 (137-152)
Blue/Black	XXXX-Large	295-340 (133-154)	58-64 (147-163)

Posey Belts are not color-coded, but are sized according to this table.

Flame-retardant fabric is available on request.

Patient weight and size are a general indicator only. Consider individual physical characteristics to choose the right product for each patient. Refer to product label for specific sizing information.





© 2012 Posey Company. All rights reserved. 19200B REV B 092412